

Interior Battery	7 Ah / 12V	4 PCS	1 x Strings					
BC080482	9 Ah / 12V	8 PCS	2 x Strings					
ASAC310	3 A Max.	= 48Vdc output with 3A charging current maximum.						
(Jumper setting available from 24Vdc output to 48 or 72Vdc)								
Charger current (Maximum)		1,5 A	4,5 A	4,5 A	7,5 A	7,5 A	10,5 A	10,5 A
To install external 250W charger for		0 pcs	1 pcs	1 pcs	2 pcs	2 pcs	3 pcs	3 pcs
Battery Strings		1 x Strings	3 x Strings	5 x Strings	7 x Strings	9 x Strings	11 x Strings	13 x Strings
Opt. Battery Bank Number: BBC080482		0 x BBC080482	1 x BBC080482	2 x BBC080482	3 x BBC080482	4 x BBC080482	5 x BBC080482	6 x BBC080482
Approximately Ah number of Battery		7 Ah	25 Ah	43 Ah	61 Ah	79 Ah	97 Ah	115 Ah
LOAD	Load (%)							
150W	10%	0:58:13	4:46:17	9:09:48	13:52:27	18:48:23	23:54:29	29:08:52
300W	20%	0:27:37	2:23:15	4:39:05	7:05:48	9:40:04	12:20:08	15:04:55
375W	25%	0:21:09	1:52:15	3:39:58	5:36:38	7:39:31	9:47:11	11:58:43
450W	30%	0:16:51	1:31:22	2:59:59	4:36:13	6:17:44	8:03:18	9:52:10
600W	40%	0:11:34	1:05:16	2:09:49	3:20:13	4:34:41	5:52:16	7:12:22
750W	50%	0:08:30	0:49:49	1:39:57	2:34:50	3:33:01	4:33:44	5:36:30
900W	60%	0:06:32	0:39:44	1:20:20	2:04:56	2:52:19	3:41:50	4:33:05
1050W	70%	0:05:11	0:32:40	1:06:33	1:43:54	2:23:38	3:05:12	3:48:17
1125W	75%	0:04:40	0:29:54	1:01:07	1:35:35	2:12:17	2:50:42	3:30:31
1200W	80%	0:04:13	0:27:30	0:56:24	1:28:22	2:02:25	2:38:06	3:15:05
1350W	90%	0:03:29	0:23:33	0:48:39	1:16:28	1:46:09	2:17:18	2:49:36
1500W	100%	0:02:55	0:20:28	0:42:33	1:07:06	1:33:20	2:00:53	2:29:29